ASCII and code-point reference card

All 128 ASCII code points with decimal, hex, category and UTF-8 width

v1.0 · devtoolbox.com/downloads/ascii.pdf · 2026-11-03

DEC	HEX	CHAR OR NAME	CATEGORY	UTF-8 BYTES
0	0x00	NUL	Control	1
1	0x01	SOH	Control	1
2	0x02	STX	Control	1
3	0x03	ETX	Control	1
4	0x04	EOT	Control	1
5	0x05	ENQ	Control	1
6	0x06	ACK	Control	1
7	0x07	BEL	Control	1
8	0x08	BS	Control	1
9	0x09	TAB	Control	1
10	0x0A	LF	Control	1
11	0x0B	VT	Control	1
12	0x0C	FF	Control	1
13	0x0D	CR	Control	1
14	0x0E	SO	Control	1
15	0x0F	SI	Control	1
16	0x10	DLE	Control	1
17	0x11	DC1	Control	1
18	0x12	DC2	Control	1
19	0x13	DC3	Control	1
20	0x14	DC4	Control	1
21	0x15	NAK	Control	1
22	0x16	SYN	Control	1
23	0x17	ETB	Control	1
24	0x18	CAN	Control	1
25	0x19	EM	Control	1
26	0x1A	SUB	Control	1
27	0x1B	ESC	Control	1
28	0x1C	FS	Control	1
29	0x1D	GS	Control	1
30	0x1E	RS	Control	1
31	0x1F	US	Control	1
32	0x20	(space)	Whitespace	1
33	0x21	!	Punctuation	1
34	0x22	"	Punctuation	1
35	0x23	#	Punctuation	1
36	0x24	$	Punctuation	1
37	0x25	%	Punctuation	1
38	0x26	&	Punctuation	1
39	0x27	'	Punctuation	1
40	0x28	(	Punctuation	1
41	0x29	)	Punctuation	1
42	0x2A	*	Punctuation	1
43	0x2B	+	Punctuation	1
44	0x2C	,	Punctuation	1
45	0x2D	-	Punctuation	1

ASCII and code-point reference card (continued)

DEC	HEX	CHAR OR NAME	CATEGORY	UTF-8 BYTES
46	0x2E	.	Punctuation	1
47	0x2F	/	Punctuation	1
48	0x30	0	Digit	1
49	0x31	1	Digit	1
50	0x32	2	Digit	1
51	0x33	3	Digit	1
52	0x34	4	Digit	1
53	0x35	5	Digit	1
54	0x36	6	Digit	1
55	0x37	7	Digit	1
56	0x38	8	Digit	1
57	0x39	9	Digit	1
58	0x3A	:	Punctuation	1
59	0x3B	;	Punctuation	1
60	0x3C	<	Punctuation	1
61	0x3D	=	Punctuation	1
62	0x3E	>	Punctuation	1
63	0x3F	?	Punctuation	1
64	0x40	@	Punctuation	1
65	0x41	A	Uppercase	1
66	0x42	B	Uppercase	1
67	0x43	C	Uppercase	1
68	0x44	D	Uppercase	1
69	0x45	E	Uppercase	1
70	0x46	F	Uppercase	1
71	0x47	G	Uppercase	1
72	0x48	H	Uppercase	1
73	0x49	I	Uppercase	1
74	0x4A	J	Uppercase	1
75	0x4B	K	Uppercase	1
76	0x4C	L	Uppercase	1
77	0x4D	M	Uppercase	1
78	0x4E	N	Uppercase	1
79	0x4F	O	Uppercase	1
80	0x50	P	Uppercase	1
81	0x51	Q	Uppercase	1
82	0x52	R	Uppercase	1
83	0x53	S	Uppercase	1
84	0x54	T	Uppercase	1
85	0x55	U	Uppercase	1
86	0x56	V	Uppercase	1
87	0x57	W	Uppercase	1
88	0x58	X	Uppercase	1
89	0x59	Y	Uppercase	1
90	0x5A	Z	Uppercase	1
91	0x5B	[	Punctuation	1
92	0x5C	\	Punctuation	1
93	0x5D	]	Punctuation	1
94	0x5E	^	Punctuation	1
95	0x5F	_	Punctuation	1

ASCII and code-point reference card (continued)

DEC	HEX	CHAR OR NAME	CATEGORY	UTF-8 BYTES
96	0x60	`	Punctuation	1
97	0x61	a	Lowercase	1
98	0x62	b	Lowercase	1
99	0x63	c	Lowercase	1
100	0x64	d	Lowercase	1
101	0x65	e	Lowercase	1
102	0x66	f	Lowercase	1
103	0x67	g	Lowercase	1
104	0x68	h	Lowercase	1
105	0x69	i	Lowercase	1
106	0x6A	j	Lowercase	1
107	0x6B	k	Lowercase	1
108	0x6C	l	Lowercase	1
109	0x6D	m	Lowercase	1
110	0x6E	n	Lowercase	1
111	0x6F	o	Lowercase	1
112	0x70	p	Lowercase	1
113	0x71	q	Lowercase	1
114	0x72	r	Lowercase	1
115	0x73	s	Lowercase	1
116	0x74	t	Lowercase	1
117	0x75	u	Lowercase	1
118	0x76	v	Lowercase	1
119	0x77	w	Lowercase	1
120	0x78	x	Lowercase	1
121	0x79	y	Lowercase	1
122	0x7A	z	Lowercase	1
123	0x7B	{	Punctuation	1
124	0x7C	|	Punctuation	1
125	0x7D	}	Punctuation	1
126	0x7E	~	Punctuation	1
127	0x7F	DEL	Control	1

NOTES

U+0000 to U+007F encode as one UTF-8 byte; every code point above that needs two or more.

U+007F is DEL, a control character, not a printable glyph.

LF (10) and CR (13) are the only line endings this table needs to disambiguate: CRLF is both bytes in that order.